

Item no.: 376859

## MCE359 - Maclean PIR motion sensor, ceiling mounted, range 6m, max load 300/150W

from **4,38 EUR**

Item no.: 376859  
shipping weight: 0.20 kg  
Manufacturer: Maclean Brackets



### Product Description

Maclean MCE359 Multifunctional flush-mounted switch with motion sensor, equipped with a high-sensitivity infrared detector. MCE359 is a device with a wide range of functionality to save electricity. It is designed for automatic control of lighting in homes, hotels, offices, staircases, corridors, basements, toilets, etc. Thanks to the infrared sensor, the product allows automatic switching of the load when motion is detected in the detection field. The device can operate both at night and during the day. The TIME knob is used to adjust the lighting time (from about 10 sec to 7 minutes). The LUX knob is used to set the ambient light sensitivity (range from 3 to 2000 LUX). When the ambient light is insufficient and you want the device to work both day and night, set the knob to the day position (sun icon). When the ambient light is less than 3 LUX, the dial should be set to the night position (moon icon). Specifications- Voltage: 110-240 V/AC- Power frequency: 50/60Hz- Ambient light: <3-2000LUX (adjustable)- Time delay: min. 10 s ±3s; max. 7 min ±2min- Rated load 220-240V/AC: max: 300W (incandescent lamps); 150W (energy-saving lamps)- Rated load 110-130V/AC: max: 150W (incandescent lamps); 75W (energy-saving lamps)- Detection range: 360°- Detection distance: max. 6m- Operating temperature: from -20 to +40°C- Operating humidity: <93% RH- Power consumption: approximately 0.5 watts- Installation height: 2,2-4m- IP class : IP20- Motion detection speed : 0.6-1.5 m/s- Electric shock protection class : II Set includes- Maclean MCE359 PIR motion sensor- User manual EN- Manufacturer's packaging Features- Allows you to reduce electricity consumption- Motion detection range: max 6m radius- Maximum load: 300 W- Works with LED lighting- Detection range: 360°- Adjustable lighting time and light intensity level at which the device starts working (dusk sensor)

### Specifications

Scan this QR code to  
view the product  
All details, up-to-date  
prices and availability

