

Item no.: 389244

## AZS216FZ - 2-way splitter 5-2400 MHz AD: 16 dB

from **24,50 EUR**

Item no.: 389244  
shipping weight: 0.10 kg  
Manufacturer: Televes



### Product Description

2-way junction box with F connections, for SMATV installations. Thanks to its branch loss (16dB), it is suitable for installation on 2 to 3 floors. Due to the reduction in size of the electronic components, it has very efficient electrical behaviour. In addition, its zamak housing provides good shielding. It is designed for indoor installation, for wall, mounting plate or standard DIN rail mounting. Supplied in boxes of 10 units. Highlights- Flexibility in mounting: can be screwed to the wall, installed on mounting plates with nuts on the connections or on a standard DIN rail (with adapter no. 519901)- Convenient screwing of the cable thanks to an inclination angle of the F connectors of 10° to the installation wall- Space optimisation in enclosures and cabinets: the inputs and outputs are always on the same side- Better organisation of the installation: Allows cabling to pass through the rear- The F-series elements can be connected together with the earthing screw, so that only a single earthing cable is required- The signal level is maintained in the sockets even with long cables, thanks to a better flatness response- Outstanding reliability: Robotised manufacturing with new generation micro-components- 100% European design, quality and manufacture Features- Low through-loss- Good shielding (Class A), made of zamak- F connector with longer thread to facilitate and secure installation on a mounting plate- Indoor installation- Earthing screw included- Bidirectional DC pass-through between inputs and outputs Specification- Frequency range MHz 5 ... 2400- Number of branches 2- Floor 2 and 3- Inputs/Frequency band: TERR SAT- Pass-through attenuation dB: 2 2.5- Subscriber attenuation dB: 16 15- Decoupling of branch outputs dB :> 20 > 20- Connectors F-socket- Voltage Max. Vdc 24- Max. Current consumption mA 350- DC pass-through On.?Off.

### Specifications

Scan this QR code to  
view the product  
All details, up-to-date  
prices and availability

