

Item no.: 389377

SE33ST - 3-gang spur socket Sat2xterr. plug-in technology

from **17,64 EUR**

Item no.: 389377
 shipping weight: 0.10 kg
 Manufacturer: Televés



Product Description

Stub socket with three connections. The IEC plug for terrestrial TV is located on the bottom left-hand side, the IEC socket for FM (radio) on the bottom right-hand side; the F connection for satellite TV (SAT) is located at the top centre. The lower part of the housing frame is open. Highlights- Separation filter for terrestrial TV and satellite TV with high suppression rate: The SAT signal is filtered in the FM TV IEC connections, while the terrestrial FM/TV signal is filtered in the satellite F connection.- Robot-controlled automated production- High shielding- Excellent decoupling between outputs Features- Die-cast housing- DC feed-through from SAT connection to input- Compatible with coaxial cables with sheath diameters ranging from 5 to 6.9 mm (Ø 5...6.9 mm) Technical data Mounting - ##Number of connections- 3R plug - "IEC" coupling TV plug - "IEC" plug SAT plug - F socket Feed-through - No Frequency range VHF - MHz 5 ... 862 Decoupling VHF - dB > 10 Attenuation: R connector VHF - dB 4 Attenuation: TV connector VHF - dB --Attenuation: SAT connector VHF - dB --Frequency range TV- MHz 5 ... 862 Decoupling TV - dB > 10 Attenuation: R-connector TV - dB --Attenuation: TV-connector TV - dB 4 Attenuation: SAT-connector TV - dB --Frequency range SAT- MHz 950 ... 2400 Decoupling SAT- dB > 10 Attenuation: R connector SAT - dB --Attenuation: TV connector SAT - dB --Attenuation: SAT connector SAT - dB 1.5 DC pass-through - SAT? One. Max. Current consumption - mA 350 Physical data Net weight:- 95g Gross weight:- 95g Width:- 70mm Height:- 67mm Depth:- 36mm Main product weight:- 94g

Specifications

Scan this QR code to view the product

All details, up-to-date prices and availability

